



E-BIKE LIGHTS OUTPUT TABLE

Drive	Voltage	Power	MJ-900S	MJ-902S	MJ-906S	ME 1000	ME 2000	ME StVZO 100LUX
BOSCH								
Performance CX	12V	17W	1000LM	1500LM	1500LM	1000LM	1500LM	900LM
Active Line(ab 2017)	12V	17W	1000LM	1500LM	1500LM	1000LM	1500LM	900LM
Active Line Plus	12V	17W	1000LM	1500LM	1500LM	1000LM	1500LM	900LM
Perfomance CX(Gen3)	12V	17W	1000LM	1500LM	1500LM	1000LM	1500LM	900LM
Perfomance CX(Gen4)	12V	18W	1000LM	1600LM	1600LM	1000LM	1600LM	900LM
BROSE								
Gen1	6V	7W	600LM	600LM	600LM	600LM	600LM	×
Drive-T/Drive TF/Drive CB	6V	7W	600LM	600LM	600LM	600LM	600LM	×
S-Drive	6V	12W	1000LM	1000LM	1000LM	1000LM	1000LM	900LM
Drive-S Alu	6V	14W	1000LM	1200LM	1200LM	1000LM	1200LM	900LM
Drive-S Mag	12V	24W	1000LM	2000LM	2000LM	1000LM	2000LM	900LM
SHIMANO								
Steps EP8	12V	24W	1000LM	2000LM	2100LM	1000LM	2000LM	900LM
Steps E8000	6V	12W	1000LM	1000LM	1000LM	1000LM	1000LM	900LM
Steps E5000	12V	24W	1000LM	2000LM	2100LM	1000LM	2000LM	900LM
Steps E6100	12V	24W	1000LM	2000LM	2100LM	1000LM	2000LM	900LM
Steps E7000	12V	24W	1000LM	2000LM	2100LM	1000LM	2000LM	900LM
YAMAHA								
PW-X	6V	9W	800LM	800LM	800LM	800LM	800LM	×
PW-ST	6V	9W	800LM	800LM	800LM	800LM	800LM	×
PW-TE	6V	9W	800LM	800LM	800LM	800LM	800LM	×
PW-CE	6V	9W	800LM	800LM	800LM	800LM	800LM	×
PW-X2	6V	9W	800LM	800LM	800LM	800LM	800LM	×
PW-X87(500w/45km/h)	6V	24W	1000LM	2000LM	2100LM	1000LM	2000LM	900LM

* Data without guarantee. Power and voltage may vary depending on the drive and should be checked individually.

* Our e-bike lights are powered by the motor of an e-bike and need to be manually installed. Proper installation may require some disassembly of the bike and motor(depending on make and model/battery type) and additional wiring to connect the light to the motor. Please contact the e-bike or motor manufacturer for installation instructions. Please note: Any disassembly may void the warranty of your e-bike. It is highly recommended to have a trained e-bike professional install your lights for you.